

# SIPROTEC

## Differential Protection 7SD5 7SD6

Communication module

DNP 3.0

Bus mapping / Point lists

---

Preface

Table of Contents

---

Notes to SIPROTEC® objects

---

1

DNP V3.0 Device Profile

---

2

Point lists

---

3

Glossary

---

Index

---

Revision: 1.0

Edition: May 2003

C53000-L1840-A014-03

---

**Liability statement**

We have checked the contents of this manual against the described hardware and software. Nevertheless, deviations may occur so that we cannot guarantee the entire harmony with the product.

The contents of this manual will be checked in periodical intervals, corrections will be made in the following editions. We look forward to your suggestions for improvement.

We reserve the right to make technical improvements without notice.

1.01.00

**Copyright**

Copyright © SIEMENS AG 2003. All rights reserved.

Copying of this document and giving it to others and the use or communication of the contents thereof, are forbidden without express authority. Offenders are liable to the payment of damages. All rights are reserved, especially in the event of grant of a patent or registration of a utility model or design.

**Registered trademarks**

SIPROTEC, SINAUT, SICAM, and DIGSI are registered trademarks of SIEMENS AG. Other names and terms can be trademarks the use of which may violate the rights of thirds.

# Preface

**Aim of This Manual** The manual is divided into the following topics:

- Notes to SIPROTEC® objects
- DNP V3.0 Device Profile
- Point lists

General information about design, configuration, and operation of SIPROTEC® devices are laid down in the SIPROTEC® 4 system manual, order no. E50417-H1176-C151.

**Target Audience** Protection engineers, commissioning engineers, persons who are involved in setting, testing and service of protection, automation, and control devices, as well as operation personnel in electrical plants and power stations.

**Additional literature** This manual describes the DNP 3.0 Device Profile of the SIPROTEC® devices.

The following additional manuals inform you about the DNP point lists and the function, operation, assembly and commissioning of the SIPROTEC® devices:

Manual	Contents	Order number
Differential Protection SIPROTEC 7SD5	Function, operation, assembly and commissioning of the SIPROTEC® device 7SD5	C53000-G1176-C119-2
Differential Protection SIPROTEC 7SD6	Function, operation, assembly and commissioning of the SIPROTEC® device 7SD6	C53000-G1176-C133-2
DNP 3.0 Communication Database	DNP communication database of the SIPROTEC® devices	C53000-L1840-A001-03

The DNP V3.0 specification and the structure of the DNP messages are defined in:

- > DNP V3.00 Subset Definitions  
Edition 2.00, November 1995  
DNP Users Group,  
Document Nr.: P009-OIG.SUB
- > DNP V3.00 Data Object Library  
Edition 0.02, July 1997  
DNP Users Group  
Document Nr.: P009-OBL

- > DNP V3.00 Data Link Layer  
Edition 0.02, May 1997  
DNP Users Group  
Document Nr.: P009-OPD.DL
- > DNP V3.00 Application Layer  
Edition 0.03, May 1997  
DNP Users Group  
Document Nr.: P009-OPD.APP
- > DNP V3.00 Transport Functions  
Edition 0.01, May 1997  
DNP Users Group  
Document Nr.: P009-OPD.TF

**Applicability of this Manual**

This manual is valid for

- SIPROTEC® devices 7SD5 7SD6 with
  - firmware version 4.2 or higher and
  - DNP communication module version 02.00.01 or higher.

For device parameterization **DIGSI® 4 version 4.3 or higher** and DNP standard mappings 3-1 to 3-n (n = device type dependent number of standard mappings) have to be used.

**Additional Support**

Should further information be desired or should particular problems arise which are not covered sufficiently for the purchaser's purpose, the matter should be referred to the local Siemens representative.

**Training Courses**

Individual course offerings may be found in our Training Catalogue, or questions may be directed to our training center. Please contact your Siemens representative.

**Instructions and Warnings**

The warnings and notes contained in this manual serve for your own safety and for an appropriate lifetime of the device. Please observe them!

The following terms are used:

**DANGER**

indicates that death, severe personal injury or substantial property damage will result if proper precautions are not taken.

**Warning**

indicates that death, severe personal injury or substantial property damage can result if proper precautions are not taken.

**Caution**

indicates that minor personal injury or property damage can result if proper precautions are not taken. This particularly applies to damage on or in the device itself and consequential damage thereof.

*Note*

indicates information about the device or respective part of the instruction manual which is essential to highlight.



## Warning!

Hazardous voltages are present in this electrical equipment during operation. Non-observance of the safety rules can result in severe personal injury or property damage.

Only qualified personnel shall work on and around this equipment after becoming thoroughly familiar with all warnings and safety notices of this manual as well as with the applicable safety regulations.

The successful and safe operation of this device is dependent on proper handling, installation, operation, and maintenance by qualified personnel under observance of all warnings and hints contained in this manual.

In particular the general erection and safety regulations (e.g. IEC, DIN, VDE, EN or other national and international standards) regarding the correct use of hoisting gear must be observed. Non-observance can result in death, personal injury or substantial property damage.

### QUALIFIED PERSONNEL

For the purpose of this instruction manual and product labels, a qualified person is one who is familiar with the installation, construction and operation of the equipment and the hazards involved. In addition, he has the following qualifications:

- Is trained and authorized to energize, de-energize, clear, ground and tag circuits and equipment in accordance with established safety practices.
- Is trained in the proper care and use of protective equipment in accordance with established safety practices.
- Is trained in rendering first aid.

### Typographic and Symbol Conventions

The following text formats are used when literal information from the device or to the device appear in the text flow:

**Parameter names**, i.e. designators of configuration or function parameters which may appear word-for-word in the display of the device or on the screen of a personal computer (with operation software DIGSI<sup>®</sup> 4), are marked in bold letters of a monospace type style.

**Parameter options**, i.e. possible settings of text parameters, which may appear word-for-word in the display of the device or on the screen of a personal computer (with operation software DIGSI<sup>®</sup> 4), are written in italic style, additionally.

“Annunciations”, i.e. designators for information, which may be output by the relay or required from other devices or from the switch gear, are marked in a monospace type style in quotation marks.

Deviations may be permitted in drawings when the type of designator can be obviously derived from the illustration.



# Table of Contents

<b>Preface</b> .....	<b>0-i</b>
<b>Table of Contents</b> .....	<b>1-1</b>
<b>1 Notes to SIPROTEC® objects</b> .....	<b>1-1</b>
1.1 Binary Inputs / Annunciations .....	1-2
1.1.1 Error with a summary alarm .....	1-2
1.1.2 Alarm Summary Event.....	1-2
1.1.3 Stop Data Transmission .....	1-3
1.2 Binary Outputs / Commands .....	1-3
1.2.1 Single Commands .....	1-3
1.2.2 Control mode REMOTE.....	1-3
1.2.3 Changing the setting group .....	1-4
1.3 Analog Inputs / Measured values .....	1-4
1.4 Metered measurands.....	1-5
<b>2 DNP V3.0 Device Profile</b> .....	<b>2-1</b>
2.1 Implementation Table .....	2-2
2.2 Device Profile Document .....	2-4
<b>3 Point lists</b> .....	<b>3-1</b>
3.1 Binary Input Points .....	3-2
3.1.1 High Speed SOTF-O/C.....	3-2
3.1.2 Differential protection.....	3-2
3.1.3 Interface .....	3-2
3.1.4 Automatic recloser .....	3-3
3.1.5 Direct Transfer Trip.....	3-4
3.1.6 Time Overcurrent protection.....	3-4
3.1.7 Thermal overload protection.....	3-5
3.1.8 Circuit breaker test .....	3-5
3.1.9 Measurement supervision .....	3-5
3.1.10 Diagnosis / General alarms .....	3-5
3.1.11 Internal mode status .....	3-6
3.1.12 Double commands - checkback signals and status.....	3-6
3.1.13 Setting group .....	3-6
3.1.14 User-allocated single-point indications .....	3-7

3.2	<b>Control Relay Output Blocks/Binary Output Status</b> .....	3-8
3.2.1	External commands (Double commands).....	3-8
3.2.2	Internal commands .....	3-8
3.2.3	User-allocated single commands.....	3-8
3.3	Analog Inputs.....	3-10
3.3.1	Recorded measured values.....	3-10
3.3.2	Statistic values.....	3-10
 <b>Glossary</b> .....		<b>G-1</b>
 <b>Index</b> .....		<b>1-1</b>



# Notes to SIPROTEC® objects

# 1

This chapter contains notes for the use and evaluation of certain SIPROTEC® objects which are available via DNP3.0 communication.

1.1	Binary Inputs / Annunciations	1-2
1.2	Binary Outputs / Commands	1-3
1.3	Analog Inputs / Measured values	1-4
1.4	Metered measurands	1-5



*Note*

The description of the standard mappings / point lists (ref. to chap. 3) contains the pre-allocation of the mapping files at delivery or first assignment of a mapping in DIGSI® 4 to the SIPROTEC® device.

Changes of the allocation and the scaling of the measured values are possible in adaptation to the concrete installation environment (ref. to page i).

---

## 1.1 Binary Inputs / Annunciations



*Note*

Depending on the device composition and the existing protection packages not all of the indicated binary inputs or protection annunciations (and corresponding DNP points) may be available in the SIPROTEC® device

---

### 1.1.1 Error with a summary alarm

The "Error with a summary alarm" is ON if at least one of the following internal alarms assumes the value ON:

- "Error 5V", "Error neutral CT", "Error 1A/5A wrong", "Error A/D converter".

**Reference** ref to chap. 3.1.10

### 1.1.2 Alarm Summary Event

The "Alarm summary event" is indicated, if at least one of the following internal alarms assumes the ON status:

- "Error Board 1", "Error Board 2", "Error Board 3", "Error Board 4", "Error Board 5", "Error Board 6", "Error Board 7",
- "Alarm NO calibration", "Failure Battery", "Alarm Real Time Clock",
- "Failure Phase Sequence", "VT Fuse Failure", "Failure Voltage Balance", "Failure Voltage Summation Phase – Ground", "Failure General Voltage Supervision",
- "Failure Current Balance", "Failure Current Summation", "Failure General Current Supervision".

**Reference** ret. to chap. 3.1.10

### 1.1.3 Stop Data Transmission

The functionality "Stop data transmission" is not supported via DNP communication. If "Stop data transmission" is active nevertheless data via DNP will be transmitted furthermore.

The annunciation "DataStop" signals the activation of "Stop data transmission" however and can be evaluated correspondingly in the DNP master.

**Reference** ref. to chap. 3.1.11

## 1.2 Binary Outputs / Commands



### Note

The allocation of the output relays to the switching devices and to the output channels is defined during parametrization of the SIPROTEC® devices.

Depending on the device composition there may be less than indicated output relays (and corresponding DNP message points) available in the SIPROTEC® device.

### 1.2.1 Single Commands

The command output mode (*pulse output, continuous output*) is changeable for the single commands using parametrization software DIGSI® 4.

The switching direction OFF for single commands with *pulse output* is not permitted and is rejected in the SIPROTEC® device.

**Reference** ref. to chap. 3.2.3

### 1.2.2 Control mode REMOTE

Control mode with control authority is REMOTE, option of unlocked control with DNP.

- Changing the Control mode REMOTE“ to UNLOCKED permits one unlocked control operation via DNP. After execution of the command, the “Control mode REMOTE“ in the SIPROTEC® device will automatically be reset to LOCKED.
- A programmed test “Switch in position“ for unlocked control operations will always be executed.

If, after changing the “Control mode REMOTE“ to UNLOCKED, no command is received via DNP for a period of 5 minutes, then the “Control mode REMOTE“ is automatically reset to LOCKED.

**Reference** ref. to chap. 3.2.2

### 1.2.3 Changing the setting group

Switching on one setting group automatically switches off the current active setting group. Transmission of the value OFF is insignificant for the change of the setting group and is refused by the device.

A change of the setting group is only possible via DNP if the parameter **CHANGE TO ANOTHER SETTING GROUP** (parameter address = 302) has the value "Protocol".

**Reference** ref. to chap. 3.2.2

## 1.3 Analog Inputs / Measured values



### Note

Depending on the device composition not all of the indicated analog inputs (and corresponding DNP message points) may be available in the SIPROTEC® device.

---

The given scaling values for the measured values in the standard mapping apply to installations with the following nominal operating values:

Measurement: Full Scale Voltage (parameter address 1103):

- >100 ... 1000 kV

Measurement: Full Scale Current (parameter address 1104):

- >10 ... 1000 A

Product of:

- Transformers – Rated Primary Voltage (parameter address 0203) and
- Ratio factor  $V_{ph}/V_{\Delta}$  (parameter address 0211)

- >100 ... 1000 kV

Product of:

- Transformers– CT Rated primary current (parameter address 0205) and
- Ratio factor  $I_4/I_{ph}$  (parameter address 0221)

- >10 ... 1000 A

Power values:

- Product of Full Scale Voltage and Full Scale Current multiplied by  $\sqrt{3}$
  - >100 ... 1000 MW (MVAR)
- 



### Note

Changes of the scaling of the measured values are possible in adaptation to the concrete installation environment (ref. to manual "DNP 3.0 Communication Database").

---

---

## 1.4 Metered measurands

### Scaling

The scaling of the metered measurands, which are derived from measured values, refers to:

**60000 impulses per hour for V = V<sub>prim</sub> and I = I<sub>prim</sub>**

$V_{\text{prim}} = \text{Full Scale Voltage}$   
(parameter address = 1103)

$I_{\text{prim}} = \text{FULL SCALE CURRENT}$   
parameter address = 1104)

### Example

In the parameter set is configured:

$I_{\text{prim}} = 1000 \text{ A}$  and  $V_{\text{prim}} = 400.0 \text{ kV}$ ,

60000 impulses correspond so that:

$1 \text{ h} * 1000 \text{ A} * 400 \text{ kV} * \sqrt{3} = 692.82 \text{ MWh}$



#### Note

- The type of the update (cyclic, with or without deletion) and the update interval must be programmed for the metered measurands with the parametrization software DIGSI<sup>®</sup> 4.
  - The scaling of the metered measurands at binary inputs ("Wp(puls)" and "Wq(puls)") depends on the externally connected pulse generator.
-



# DNP V3.0 Device Profile

# 2

2.1	Implementation Table	2-2
2.2	Device Profile Document	2-4

## 2.1 Implementation Table

The following table gives a list of all objects recognized and returned by the SIPROTEC® device.

For static objects, requests sent with qualifiers 00, 01, 06, 07 or 08 will be responded with qualifiers 00 or 01.

Requests sent with qualifiers 17 or 28 will be responded with qualifiers 17 or 28.

For change-event objects, qualifiers 17 or 28 are always responded.

In the table below text shaded 00, 01 (start stop) indicates Subset Level 3 functionality (beyond Subset Level 2), text shaded as 07, 08 (limited qty) indicates functionality beyond Subset Level 3.

OBJECTS			REQUEST		RESPONSE	
Object	Variation	Description	Function Codes (dec)	Qualifier Codes (hex)	Function Codes (dec)	Qualifier Codes (hex)
1	0	Binary Input - Any Variations	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)		
1	2	Binary Input with Status	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)	129 (response)	00, 01 (start-stop) 17, 28 (index)
2	0	Binary Input Change - Any Variations	1 (read)	06 (no range) 07, 08 (limited qty)		
2	2	Binary Input Change with Time	1 (read)	06 (no range) 07, 08 (limited qty)	129 (response) 130 (unsol. resp)	17, 28 (index)
10	0	Binary Output - Any Variations	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)		
10	2	Binary Output with Status	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)	129 (response)	00, 01 (start-stop) 17, 28 (index)
12	1	Contol Relay Output Block	3 (select) 4 (operate) 5 (direct op.) 6 (dir. op. noack)	00, 01 (start-stop) 07, 08 (limited qty) 17, 28 (index)	129 (response)	echo of response
20	0	Binary Counter - Any Variations	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)		
20	1	32-Bit Binary Counter (with Flag)	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qty) 17, 28 (index)		
22	0	Counter Change Event - Any Variations	1 (read)	06 (no range) 07, 08 (limited qty)		
22	1	32-Bit Counter Change Event without Time	1 (read)	06 (no range) 07, 08 (limited qty)		



OBJECTS			REQUEST		RESPONSE	
Object	Variation	Description	Function Codes (dec)	Qualifier Codes (hex)	Function Codes (dec)	Qualifier Codes (hex)
30	0	16-Bit Analog Input - Any Variations	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qfy) 17, 28 (index)		
30	1	32-Bit Analog Input with Status	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qfy) 17, 28 (index)	129 (response)	00, 01 (start-stop) 17, 28 (index)
30	2	16-Bit Analog Input with Status	1 (read)	00, 01 (start-stop) 06 (no range) 07, 08 (limited qfy) 17, 28 (index)	129 (response)	00, 01 (start-stop) 17, 28 (index)
32	0	Analog Change Event - Any Variations	1 (read)	06 (no range) 07, 08 (limited qfy)		
32	1	32-Bit Analog Change Event without Time	1 (read)	06 (no range) 07, 08 (limited qfy)	129 (response) 130 (unsol. resp)	17, 28 (index)
32	2	16-Bit Analog Change Event without Time	1 (read)	06 (no range) 07, 08 (limited qfy)	129 (response) 130 (unsol. resp)	17, 28 (index)
50	1	Time and Date	2 (write)	07 (limited qfy = 1)		
60	1	Class 0 Data	1 (read)	06 (no range)		
60	2	Class 1 Data	1 (read)	06 (no range) 07, 08 (limited qfy)		
60	3	Class 2 Data	1 (read)	06 (no range) 07, 08 (limited qfy)		
60	4	Class 3 Data	1 (read)	06 (no range) 07, 08 (limited qfy)		
80	1	Internal Indications	2 (write)	00 (start-stop) (index must = 7)		

## 2.2 Device Profile Document

<h1 style="margin: 0;">DNP V3.0</h1> <h2 style="margin: 0;">DEVICE PROFILE DOCUMENT</h2>	
Vendor Name: <b>SIEMENS AG</b>	
Device Name: <b>7SD5 7SD6</b>	
Highest DNP Level Supported: For Requests    DNP-L2 For Responses   DNP-L2	Device Function: <input type="checkbox"/> Master <input checked="" type="checkbox"/> Slave
Notable objects, functions, and/or qualifiers supported in addition to the Highest DNP Levels Supported (the complete list is described in the attached table):  For static (non-change-event) object requests, request qualifier codes 00 and 01 (start-stop), 07 and 08 (limited quantity), and 17 and 28 (index) are supported in addition to request qualifier code 06 (no range). Static object requests sent with qualifiers 00, 01, 06, 07, or 08, will be responded with qualifiers 00 or 01. Static object requests sent with qualifiers 17 or 28 will be responded with qualifiers 17 or 28. For change-event object requests, qualifiers 17 or 28 are always responded.  16-bit Analog Change Events with Time may be requested.  The write function code for Object 50 (Time and Date), variation 1, is supported.  The features outlined within this Device Profile have successfully passed DNP Conformance Test of Subset Level 2 outlined in DNP3-2000 IED Certification Procedure.	
Maximum Data Link Frame Size (octets): Transmitted <u>  292  </u> Received <u>  292  </u>	Maximum Application Fragment Size (octets): Transmitted <u>  Configurable up to 2048  </u> Received <u>  2048  </u>
Maximum Data Link Re-tries: <input checked="" type="checkbox"/> None <input type="checkbox"/> Fixed at <input type="checkbox"/> Configurable, range <u>  0  </u> to <u>  255  </u>	Maximum Application Layer Re-tries: <input checked="" type="checkbox"/> None <input type="checkbox"/> Configurable, range <u>      </u> to <u>      </u> (Fixed is not permitted)
Requires Data Link Layer Confirmation: <input type="checkbox"/> Never <input type="checkbox"/> Always <input type="checkbox"/> Sometimes If 'Sometimes', when? _____ <input checked="" type="checkbox"/> Configurable If 'Configurable', how? by the protection data processing program DIGSI® 4	

Requires Application Layer Confirmation:

- Never
- Always (not recommended)
- When reporting Event Data (Slave devices only)
- When sending multi-fragment responses (Slave devices only)
- Sometimes If 'Sometimes', when? \_\_\_\_\_
- Configurable If 'Configurable', how? by the protection data processing program DIGSI® 4

Timeouts while waiting for:

- |                         |                                          |                                         |                                   |                                                  |
|-------------------------|------------------------------------------|-----------------------------------------|-----------------------------------|--------------------------------------------------|
| Data Link Confirm       | <input type="checkbox"/> None            | <input type="checkbox"/> Fixed at _____ | <input type="checkbox"/> Variable | <input checked="" type="checkbox"/> Configurable |
| Complete Appl. Fragment | <input checked="" type="checkbox"/> None | <input type="checkbox"/> Fixed at _____ | <input type="checkbox"/> Variable | <input type="checkbox"/> Configurable            |
| Application Confirm     | <input type="checkbox"/> None            | <input type="checkbox"/> Fixed at _____ | <input type="checkbox"/> Variable | <input checked="" type="checkbox"/> Configurable |
| Complete Appl. Response | <input checked="" type="checkbox"/> None | <input type="checkbox"/> Fixed at _____ | <input type="checkbox"/> Variable | <input type="checkbox"/> Configurable            |

Others: Default value are configurable by the protection data processing program DIGSI® 4

Sends/Executes Control Operations:

- |                         |                                           |                                            |                                    |                                       |
|-------------------------|-------------------------------------------|--------------------------------------------|------------------------------------|---------------------------------------|
| WRITE Binary Outputs    | <input checked="" type="checkbox"/> Never | <input type="checkbox"/> Always            | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| SELECT/OPERATE          | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| DIRECT OPERATE          | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| DIRECT OPERATE - NO ACK | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Count > 1               | <input checked="" type="checkbox"/> Never | <input type="checkbox"/> Always            | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Pulse On                | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Pulse Off               | <input checked="" type="checkbox"/> Never | <input type="checkbox"/> Always            | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Latch On                | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Latch Off               | <input type="checkbox"/> Never            | <input checked="" type="checkbox"/> Always | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Queue                   | <input checked="" type="checkbox"/> Never | <input type="checkbox"/> Always            | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |
| Clear Queue             | <input checked="" type="checkbox"/> Never | <input type="checkbox"/> Always            | <input type="checkbox"/> Sometimes | <input type="checkbox"/> Configurable |

Note:

CONTROL RELAY OUTPUT BLOCK parameters (count, on-time, off-time) are ignored.

TimeSync Information:

a.) TimeSync Period

- Never
- Fixed at \_\_\_\_\_seconds
- Configurable, range \_\_\_1\_\_\_ to \_\_86400\_\_seconds

b.) Maximum time base drift over 10 minute interval: \_\_\_\_\_30\_\_ms

c.) Maximum Internal Time Reference Error when set via DNP: \_\_\_\_\_1\_\_ms

d.) Maximum Delay Measurement error: \_\_\_\_\_20\_\_ms

e.) Maximum response time: \_\_\_\_\_100\_\_ms

c.) Event data time-tag error – if different than (c):

- Binary Input Change Events \_\_\_\_\_ms
- Counter Change Events \_\_\_\_\_ms
- Frozen Counter Change Events \_\_\_\_\_ms
- Analog Change Events \_\_\_\_\_ms
- Frozen Analog Change Events \_\_\_\_\_ms

<p>Reports Binary Input Change Events when no specific variation requested:</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> Never</li> <li><input checked="" type="checkbox"/> Only time-tagged</li> <li><input type="checkbox"/> Only non-time-tagged</li> <li><input type="checkbox"/> Configurable to send both, one or the other (attach explanation)</li> </ul>	<p>Reports time-tagged Binary Input Change Events when no specific variation requested:</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> Never</li> <li><input checked="" type="checkbox"/> Binary Input Change With Time</li> <li><input type="checkbox"/> Binary Input Change With Relative Time</li> <li><input type="checkbox"/> Configurable (attach explanation)</li> </ul>
<p>Sends Unsolicited Responses:</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> Never</li> <li><input checked="" type="checkbox"/> Configurable (Unsolicited data response mode are switched on/off via the configuration tool )</li> <li><input type="checkbox"/> Only certain objects</li> <li><input type="checkbox"/> Sometimes (attach explanation)</li> <li><input checked="" type="checkbox"/> ENABLE/DISABLE UNSOLICITED Function codes supported</li> </ul>	<p>Sends Static Data in Unsolicited Responses:</p> <ul style="list-style-type: none"> <li><input checked="" type="checkbox"/> Never</li> <li><input type="checkbox"/> When Device Restarts</li> <li><input type="checkbox"/> When Status Flags Change</li> </ul> <p>No other options are permitted.</p>
<p>Default Counter Object/Variation:</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> No Counters Reported</li> <li><input type="checkbox"/> Configurable (attach explanation)</li> <li><input checked="" type="checkbox"/> Default Object <u>  20  </u></li> <li>                  Default Variation <u>  01  </u></li> <li><input type="checkbox"/> Point-by-point list attached</li> </ul> <p>Sends 32-Bit counters.</p>	<p>Counters Roll Over at:</p> <ul style="list-style-type: none"> <li><input type="checkbox"/> No Counters Reported</li> <li><input type="checkbox"/> Configurable (attach explanation)</li> <li><input type="checkbox"/> 16 Bits</li> <li><input checked="" type="checkbox"/> 32 Bits</li> <li><input type="checkbox"/> Other Value _____</li> <li><input type="checkbox"/> Point-by-point list attached</li> </ul>
<p>Sends Multi-Fragment Responses: <input checked="" type="checkbox"/> Yes    <input type="checkbox"/> No</p>	

# Point lists

# 3

3.1	Binary Input Points	3-2
3.2	Control Relay Output Blocks/Binary Output Status	3-8
3.3	Analog Inputs	3-10

### 3.1 Binary Input Points

<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
<b>3.1.1 High Speed SOTF-O/C</b>			
0	50HS OFF	50HS High Speed SOTF-O/C is switched OFF; ON=1, OFF=0	3
1	50HS BLOCK	50HS High Speed SOTF-O/C is BLOCKED; ON=1, OFF=0	3
2	50HS ACTIVE	50HS High Speed SOTF-O/C is ACTIVE; ON=1, OFF=0	3
3	50HS PICKUP	50HS PICKED UP; ON=1, OFF=0	2
4	50HS Pickup Ph A	50HS Pickup Phase A; ON=1, OFF=0	2
5	50HS Pickup Ph B	50HS Pickup Phase B; ON=1, OFF=0	2
6	50HS Pickup Ph C	50HS Pickup Phase C; ON=1, OFF=0	2
7	I>>>>O/C p.upL1	SOFT-O/C Pickup I>>>>L1; ON=1, OFF=0	2
8	I>>>>O/C p.upL2	SOFT-O/C Pickup I>>>>L2; ON=1, OFF=0	2
9	I>>>>O/C p.upL3	SOFT-O/C Pickup I>>>>L3; ON=1, OFF=0	2
10	SOFT TRIP 1pA	SOFT O/C TRIP Only A; ON=1, OFF=0	2
11	SOFT TRIP 1pB	SOFT O/C TRIP Only B; ON=1, OFF=0	2
12	SOFT TRIP 1pC	SOFT O/C TRIP Only C; ON=1, OFF=0	2
13	SOFT TRIP 1pole	SOFT O/C TRIP 1pole; ON=1, OFF=0	2
14	50HS TRIP PhABC	50HS High Speed SOTF-O/C TRIP command; ON=1, OFF=0	2
<b>3.1.2 Differential protection</b>			
15	87 is OFF	87 is switched OFF; ON=1, OFF=0	3
16	87 is blocked	87 is BLOCKED; ON=1, OFF=0	3
17	87 active	87 is ACTIVE; ON=1, OFF=0	3
18	87 Gen. Fault	87 Fault detection; ON=1, OFF=0	2
19	87 Fault in A	87 Fault detection in Phase A; ON=1, OFF=0	2
20	87 Fault in B	87 Fault detection in Phase B; ON=1, OFF=0	2
21	87 Fault in C	87 Fault detection in Phase C; ON=1, OFF=0	2
22	87 Graund Fault	87 Graund Fault detection; ON=1, OFF=0	3
23	87 General TRIP	87 General TRIP ; ON=1, OFF=0	3
24	87 TRIP 1pole A	87 TRIP - Only A; ON=1, OFF=0	3
25	87 TRIP 1pole B	87 TRIP - Only B; ON=1, OFF=0	3
26	87 TRIP 1pole C	87 TRIP - Only C; ON=1, OFF=0	3
27	87 TRIP ABC	87 TRIP ABC; ON=1, OFF=0	3
<b>3.1.3 Interface</b>			
28	PI1 Data fault	Prot. Interface 1: Recept. of fault data; ON=1, OFF=0	3

<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
29	PI1 Data failure	Prot. Interface 1: Total receipt. failure ; ON=1, OFF=0	3
30	PI2 Data fault	Prot. Interface 2: Recept. of fault data; ON=1, OFF=0	3
31	PI2 Data failure	Prot. Interface 2: Total receipt. failure ; ON=1, OFF=0	3
32	PI1 TD alarm	Prot. Interface 1: Dev. Time Offset alarm; ON=1, OFF=0	3
33	PI2 TD alarm	Prot. Interface 2: Dev. Time Offset alarm; ON=1, OFF=0	3
<b>3.1.4 Automatic recloser</b>			
34	79 ON	79 Auto recloser is switched ON; ON=1, OFF=0	2
35	79 is blocked	79: Auto recloser is blocked; ON=1, OFF=0	2
36	79 not ready	79: Auto recloser is not ready; ON=1, OFF=0	2
37	CB not ready	79: Circuit breaker 1 not ready; ON=1, OFF=0	2
38	79 T-CBreadyExp	79: CB ready monitoring window expired; ON=1, OFF=0	3
39	79 in progress	79 - in progress; ON=1, OFF=0	2
40	79 T-Start Exp	79: Start-signal monitoring time expired; ON=1, OFF=0	3
41	79 TdeadMax Exp	79: Maximum dead time expired; ON=1, OFF=0	3
42	79 Evolving Flt	79: Evolving fault recognition; ON=1, OFF=0	3
43	79 Program1pole	79 is set to operate after 1p trip only; ON=1, OFF=0	3
44	79 Td. evol.Flt	79 dead time after evolving fault; ON=1, OFF=0	3
45	79 Tdead 1pTrip	79 dead time after 1pole trip running; ON=1, OFF=0	3
46	79 Tdead 3pTrip	79 dead time after 3pole trip running; ON=1, OFF=0	3
47	79 Tdead 1pFlt	79 dead time after 1phase fault running; ON=1, OFF=0	3
48	79 Tdead 2pFlt	79 dead time after 2phase fault running; ON=1, OFF=0	3
49	79 Tdead 3pFlt	79 dead time after 3phase fault running; ON=1, OFF=0	3
50	79 1stCyc. run.	79 1st cycle running; ON=1, OFF=0	3
51	79 2ndCyc. run.	79 2nd cycle running; ON=1, OFF=0	3
52	79 3rdCyc. run.	79 3rd cycle running; ON=1, OFF=0	3
53	79 4thCyc. run.	79 4th or higher cycle running; ON=1, OFF=0	3
54	79 ATD run.	79 cycle is running in ATD mode; ON=1, OFF=0	3
55	79 Close	79 Close command; ON=1, OFF=0	3
56	79 Close1.Cyc1p	79: Close command after 1pole, 1st cycle; ON=1, OFF=0	3
57	79 Close1.Cyc3p	79: Close command after 3pole, 1st cycle; ON=1, OFF=0	3
58	79 Close 2.Cyc	79: Close command 2nd cycle (and higher) ; ON=1, OFF=0	3
59	79 T-Recl. run.	79: Reclaim time is running; ON=1, OFF=0	3
60	79 Successful	79 - cycle successful; ON=1, OFF=0	3
61	79 Lockout	79 - cycle lockout; ON=1, OFF=0	3

<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
62	79 1p Trip Perm	79: 1pole trip permitted by internal AR; ON=1, OFF=0	3
63	79 TRIP 3pole	79: TRIP command 3pole; ON=1, OFF=0	2
64	79 1.CycZoneRel	79 1st cycle zone extension release; ON=1, OFF=0	3
65	79 2.CycZoneRel	79 2nd cycle zone extension release; ON=1, OFF=0	3
66	79 3.CycZoneRel	79 3rd cycle zone extension release; ON=1, OFF=0	3
67	79 4.CycZoneRel	79 4th cycle zone extension release; ON=1, OFF=0	3
68	79 Zone Release	79 zone extension (general) ; ON=1, OFF=0	3
69	79 Remote Close	79: Remote close signal send; ON=1, OFF=0	3
<b>3.1.5 Direct Transfer Trip</b>			
70	DTT OFF	Direct Transfer Trip is switched OFF; ON=1, OFF=0	3
71	DTT BLOCK	Direct Transfer Trip is BLOCKED; ON=1, OFF=0	3
72	DTT TRIP 1p. Ph A	DTT TRIP command - Only Phase A; ON=1, OFF=0	2
73	DTT TRIP 1p. Ph B	DTT TRIP command - Only Phase B; ON=1, OFF=0	2
74	DTT TRIP 1p. Ph C	DTT TRIP command - Only Phase C; ON=1, OFF=0	2
75	DTT TRIP Ph ABC	DTT TRIP command Phases ABC; ON=1, OFF=0	2
<b>3.1.6 Time Overcurrent protection</b>			
76	5X-B OFF	50(N)/51(N) Backup O/C is switched OFF; ON=1, OFF=0	3
77	5X-B BLOCK	50(N)/51(N) Backup O/C is BLOCKED; ON=1, OFF=0	3
78	5X-B ACTIVE	50(N)/51(N) Backup O/C is ACTIVE; ON=1, OFF=0	3
79	5X-B PICKUP	50(N)/51(N) Backup O/C PICKED UP; ON=1, OFF=0	2
80	5X-B Pickup Ph A	50(N)/51(N) Backup O/C PICKUP Phase A; ON=1, OFF=0	3
81	5X-B Pickup Ph B	50(N)/51(N) Backup O/C PICKUP Phase B; ON=1, OFF=0	3
82	5X-B Pickup Ph C	50(N)/51(N) Backup O/C PICKUP Phase C; ON=1, OFF=0	3
83	5X-B Pickup Gnd	50(N)/51(N) Backup O/C PICKUP GROUND; ON=1, OFF=0	3
84	50(N)-B1 PICKUP	50(N)-B1 Pickup; ON=1, OFF=0	3
85	50(N)-B2 PICKUP	50(N)-B2 Pickup; ON=1, OFF=0	3
86	51(N)-B PICKUP	51(N)-B Pickup; ON=1, OFF=0	3
87	50-STUB PICKUP	50-STUB Pickup; ON=1, OFF=0	3
88	5X-B TRIP	50(N)/51(N)-B General TRIP command; ON=1, OFF=0	2
89	5X-B TRIP 1p. Ph A	50(N)/51(N)-B TRIP - Only Phase A; ON=1, OFF=0	2
90	5X-B TRIP 1p. Ph B	50(N)/51(N)-B TRIP - Only Phase B; ON=1, OFF=0	2
91	5X-B TRIP 1p. Ph C	50(N)/51(N)-B TRIP - Only Phase C; ON=1, OFF=0	2
92	5X-B TRIP ABC	50(N)/51(N)-B TRIP Phases ABC; ON=1, OFF=0	2
93	50(N)-B1 TRIP	50(N)-B1 TRIP; ON=1, OFF=0	3



<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
94	50(N)-B2 TRIP	50(N)-B2 TRIP; ON=1, OFF=0	3
95	51(N)-B TRIP	51(N)-B TRIP; ON=1, OFF=0	3
96	50-STUB TRIP	50-STUB TRIP; ON=1, OFF=0	3
<b>3.1.7 Thermal overload protection</b>			
97	49 O / L OFF	49 Overload Protection is OFF; ON=1, OFF=0	3
98	49 O/L BLOCK	49 Overload Protection is BLOCKED; ON=1, OFF=0	3
99	49 O/L ACTIVE	49 Overload Protection is ACTIVE; ON=1, OFF=0	3
100	49 O/L I Alarm	49 Overload Current Alarm (I alarm) ; ON=1, OFF=0	1
101	49 O/L Alarm	49 Overload Alarm! Near Thermal Trip; ON=1, OFF=0	1
102	49 Winding O/L	49 Winding Overload; ON=1, OFF=0	3
103	49 Th O/L TRIP	49 Thermal Overload TRIP; ON=1, OFF=0	2
<b>3.1.8 Circuit breaker test</b>			
104	CB1-TESTtrip PhA	CB1-TEST TRIP command - Only Phase A; ON=1, OFF=0	3
105	CB1-TESTtrip PhB	CB1-TEST TRIP command - Only Phase B; ON=1, OFF=0	3
106	CB1-TESTtrip PhC	CB1-TEST TRIP command - Only Phase C; ON=1, OFF=0	3
107	CB1-TESTtripABC	CB1-TEST TRIP command ABC; ON=1, OFF=0	3
108	CB1-TEST close	CB1-TEST CLOSE command; ON=1, OFF=0	3
109	CB-TEST running	CB-TEST is in progress; ON=1, OFF=0	3
<b>3.1.9 Measurement supervision</b>			
110	Fail I Superv.	Failure: general Current Supervision; ON=1, OFF=0	3
111	Fail I balance	Failure: Current Balance; ON=1, OFF=0	1
112	Fail V Superv.	Failure: general Voltage Supervision; ON=1, OFF=0	1
113	Fail V balance	Failure: Voltage Balance; ON=1, OFF=0	1
114	MeasSup OFF	Measurement Supervision is switched OFF; ON=1, OFF=0	3
115	Failure Sum I	Alarm: Current summation supervision ; ON=1, OFF=0	1
116	Broken Iwire L1	Alarm: Broken current-wire detected L1; ON=1, OFF=0	3
117	Broken Iwire L2	Alarm: Broken current-wire detected L2; ON=1, OFF=0	1
118	Broken Iwire L3	Alarm: Broken current-wire detected L3; ON=1, OFF=0	3
<b>3.1.10 Diagnosis / General alarms</b>			
119	Device OK	Device is operational and protecting; ON=1, OFF=0	1
120	ProtActive	At least one protection funct. is active; ON=1, OFF=0	2
121	Settings Calc.	Setting calculation is running; ON=1, OFF=0	3
122	Error Sum Alarm	Error with a summary alarm; ON=1, OFF=0 (ref. to chap. 1.1.1)	2

<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
123	Alarm Sum Event	Alarm Summary Event; ON=1, OFF=0 (ref. to chap. 1.1.2)	2
124	Error A/D conv.	Error A/D converter; ON=1, OFF=0	2
125	Relay PICKUP	Relay PICKUP; ON=1, OFF=0	1
126	Relay PICKUP PhA	Relay PICKUP Phase A; ON=1, OFF=0	1
127	Relay PICKUP PhB	Relay PICKUP Phase B; ON=1, OFF=0	1
128	Relay PICKUP PhC	Relay PICKUP Phase C; ON=1, OFF=0	1
129	Relay PICKUP G	Relay PICKUP GROUND; ON=1, OFF=0	1
130	Relay TRIP	Relay GENERAL TRIP command; ON=1, OFF=0	1
131	Definitive TRIP	Relay Definitive TRIP; ON=1, OFF=0	1
132	Relay TRIP PhA	Relay TRIP command Phase A; ON=1, OFF=0	1
133	Relay TRIP PhB	Relay TRIP command Phase B; ON=1, OFF=0	1
134	Relay TRIP PhC	Relay TRIP command Phase C; ON=1, OFF=0	1
135	Emer. mode	Emergency mode; ON=1, OFF=0	1
<b>3.1.11 Internal mode status</b>			
136	DataStop	Stop data transmission; ON=1, OFF=0 (ref. to chap. 1.1.3)	3
137	Test mode	Test mode; ON=1, OFF=0	3
138	Chatter ON	Chatter ON; ON=1, OFF=0	3
139	Man.Clos.Detect	Manual close signal detected; ON=1, OFF=0	2
140	LOCKOUT	LOCKOUT is active; ON=1, OFF=0	1
<b>3.1.12 Double commands - checkback signals and status</b>			
141	Switch 1	Input state of Switch 1; 0 = open, 1 = close	1
142	Switch 1 status	Switch 1 failure status; 0 = switch position is open or close, 1 = switch is in an intermediate position or position state is incorrect.	1
143	Switch 2	Input state of Switch 2; 0 = open, 1 = close	1
144	Switch 2 status	Switch 2 failure status; 0 = switch position is open or close, 1 = switch is in an intermediate position or position state is incorrect.	1
145	Switch 3	Input state of ground Switch 3; 0 = open, 1 = close	1
146	Switch 3 status	Switch 3 failure status; 0 = switch position is open or close, 1 = switch is in an intermediate position or position state is incorrect.	1
147	Switch 4	Input state of Switch 4; 0 = open, 1 = close	1
148	Switch 4 status	Switch 4 failure status; 0 = switch position is open or close, 1 = switch is in an intermediate position or position state is incorrect.	1
<b>3.1.13 Setting group</b>			
149	Group A	Setting Group A; ON=1, OFF=0	1

<b>Binary Input Points</b>			
Static (Steady-State) Object Number: <b>1</b>			
Change Event Object Number: <b>2</b>			
Request Function Codes supported: <b>1 (read)</b>			
Static Variation reported when variation 0 requested: <b>1 (Binary Input with status)</b>			
Change Event Variation reported when variation 0 requested: <b>2 (Binary Input Change with Time)</b>			
Point Index	Name	Description	Class
150	Group B	Setting Group B; ON=1, OFF=0	1
151	Group C	Setting Group C; ON=1, OFF=0	1
152	Group D	Setting Group D; ON=1, OFF=0	1
<b>3.1.14 User-allocated single-point indications</b>			
153	<unnamed>*	User input 1	2
154	<unnamed>	User input 2	2
155	<unnamed>	User input 3	2
156	<unnamed>	User input 4	2
157	<unnamed>	User input 5	2
158	<unnamed>	User input 6	2
159	<unnamed>	User input 7	2
160	<unnamed>	User input 8	2
161	<unnamed>	User input 9	2
162	<unnamed>	User input 10	2
163	<unnamed>	User input 11	2
164	<unnamed>	User input 12	2
165	<unnamed>	User input 13	2
166	<unnamed>	User input 14	2
167	<unnamed>	User input 15	2

\*The names are defined during indication allocation using parametrization software DIGSI® 4

## 3.2 Control Relay Output Blocks/Binary Output Status

Point Index	Name	Description	Supported Control Relay Output Block Fields
<b>Binary Output Status Points</b>			
Object Number: 10			
Request Function Codes supported: 1 (Read)			
Default Variation reported when variation 0 requested: 2 (Binary Output Status)			
<b>Control Relay Output Blocks/Binary Output Status</b>			
Object Number: 12			
Request Function Codes supported: 3 (select), 4 (operate), 5 (direct operate), 6 (direct operate, no ack)			
<b>3.2.1 External commands (Double commands)</b>			
0	Switch 1	Trip Switch 1	Trip, Pulse On (On-Time Fixed)
1	Switch 1	Close Switch 1	Close, Pulse On (On-Time Fixed)
2	Switch 2	Trip Switch 2	Trip, Pulse On (On-Time Fixed)
3	Switch 2	Close Switch 2	Close, Pulse On (On-Time Fixed)
4	Switch 3	Trip Switch 3	Trip, Pulse On (On-Time Fixed)
5	Switch 3	Close Switch 3	Close, Pulse On (On-Time Fixed)
6	Switch 4	Trip Switch 4	Trip, Pulse On (On-Time Fixed)
7	Switch 4	Close Switch 4	Close, Pulse On (On-Time Fixed)
<b>3.2.2 Internal commands</b>			
8	79 ON	Activation / deactivation of Auto-reclosure function	Latch On, Latch Off
9	ProtActive	Protection activation / deactivation	Latch On, Latch Off
10	Group A	Select setting group A and deactivate setting group B,C,D (ref. to chap. 1.2.3)	Latch On
11	Group B	Select setting group B and deactivate setting group A,C,D	Latch On
12	Group C	Select setting group C and deactivate setting group A,B,D	Latch On
13	Group D	Select setting group D and deactivate setting group A,B,C	Latch On
14	Test 87	87 Set test state of 87; ON=1, OFF=0	Latch On; Latch Off
15	Commiss. 87	87 Set commissioning state of 87; ON=1, OFF=0	Latch On; Latch Off
16	Logout	Local activation of Logout state; ON=1, OFF=0	Latch On; Latch Off
17	ModeREMOTE	Mode remote control; UNLOCKED=1, LOCKED=0 (ref. to chap. 1.2.2)	Latch On; Latch Off
<b>3.2.3 User-allocated single commands</b>			
Please ref. to chap. 1.2.1 for additional notes.			

**Binary Output Status Points**Object Number: **10**Request Function Codes supported: **1 (Read)**Default Variation reported when variation 0 requested: **2 (Binary Output Status)****Control Relay Output Blocks/Binary Output Status**Object Number: **12**Request Function Codes supported: **3 (select), 4 (operate), 5 (direct operate),  
6 (direct operate, no ack)**

Point Index	Name	Description	Supported Control Relay Output Block Fields
18	<unnamed> <sup>†</sup>	User output 1	Latch On, Latch Off
19	<unnamed>	User output 2	Latch On, Latch Off
20	<unnamed>	User output 3	Latch On, Latch Off
21	<unnamed>	User output 4	Latch On, Latch Off
22	<unnamed>	User output 5	Latch On, Latch Off
23	<unnamed>	User output 6	Latch On, Latch Off
24	<unnamed>	User output 7	Latch On, Latch Off
25	<unnamed>	User output 8	Latch On, Latch Off
26	<unnamed>	User output 9	Latch On, Latch Off
27	<unnamed>	User output 10	Latch On, Latch Off

\*The On-Time is fixed within the SIPROTEC<sup>®</sup> parameter package for each common object.  
The Control Relay Output Block information on-time will be ignored.

<sup>†</sup>The names are defined during indication allocation using parametrization software DIGSI<sup>®</sup> 4

### 3.3 Analog Inputs

<b>Analog Inputs</b>				
Static (Steady-State) Object Number: <b>30</b>				
Change Event Object Number: <b>32</b>				
Request Function Codes supported: <b>1 (read)</b>				
Static Variation reported when variation 0 requested: <b>02 (16-Bit Analog Input)</b>				
Change Event Variation reported when variation 0 requested: <b>02 (Analog Change Event without Time)</b>				
Point Index	Name	Description	Scaling(32767 corresponds to ...)	Default Change Event assigned Class
<b>3.3.1 Recorded measured values</b>				
0	la =	la	3276.7 A	1
1	lb =	lb	3276.7 A	1
2	lc =	lc	3276.7 A	1
3	3lo =	3lo (zero sequence)	3276.7 A	2
4	Freq=	Frequency	327.67 Hz	1
5	IDiff A=	IDiff A (% Operation nominal current)	327,67 %	1
6	IDiff B=	IDiff B (% Operation nominal current)	327,67 %	1
7	IDiff C=	IDiff C (% Operation nominal current)	327,67 %	1
8	IRest A=	IRest A (% Operation nominal current)	327,67 %	1
9	IRest B=	IRest B (% Operation nominal current)	327,67 %	1
10	IRest C=	IRest C (% Operation nominal current)	327,67 %	1
11	PI1 TD	Prot. Interface 1: Transmission delay	327,67 ms	3
12	PI2 TD	Prot. Interface 2: Transmission delay	327,67 ms	3
13	PI1 A/m	Prot. Interface 1: Availability per min.	327,67 %	3
14	PI1 A/h	Prot. Interface 1: Availability per hour	327,67 %	3
15	PI2 A/m	Prot. Interface 2: Availability per min.	327,67 %	3
16	PI2 A/h	Prot. Interface 2: Availability per hour	327,67 %	3
17	<unnamed>	User input 1		2
18	<unnamed>	User input 2		2
19	<unnamed>	User input 3		2
20	<unnamed>	User input 4		2
21	<unnamed>	User input 5		2
<b>If Object 30 Variation 01 (32-Bit Analog Input) requesten, additional:</b>				
<b>3.3.2 Statistic values</b>				
22	# TRIPs=	Number of breaker TRIP commands		3
23	# TRIPs PhA=	Number of breaker TRIP commands, Ph A		3
24	# TRIPs PhB=	Number of breaker TRIP commands, Ph B		3
25	# TRIPs PhC=	Number of breaker TRIP commands, Ph C		3

<b>Analog Inputs</b>				
Static (Steady-State) Object Number: <b>30</b>				
Change Event Object Number: <b>32</b>				
Request Function Codes supported: <b>1 (read)</b>				
Static Variation reported when variation 0 requested: <b>02 (16-Bit Analog Input)</b>				
Change Event Variation reported when variation 0 requested: <b>02 (Analog Change Event without Time)</b>				
Point Index	Name	Description	Scaling(32767 corresponds to ...)	Default Change Event assigned Class
26	Sum Ia =	Accumulation of interrupted current Ph A	327.67 kA	3
27	Sum Ib =	Accumulation of interrupted current Ph B	327.67 kA	3
28	Sum Ic =	Accumulation of interrupted current Ph C	327.67 kA	3





# Glossary

<b>AME</b>	<b>A</b> synchronous interface <b>m</b> odule with ( <b>e</b> lectrical) isolated RS485 interface for the SIPROTEC devices from Siemens.
<b>AMO</b>	<b>A</b> synchronous interface <b>m</b> odule with <b>o</b> ptical interface for the SIPROTEC devices from Siemens.
<b>AR</b>	<b>A</b> utomatic <b>R</b> ecloser
<b>CFC</b>	<b>C</b> ontinuous <b>F</b> unction <b>C</b> hart
<b>DC</b>	<b>D</b> ouble <b>C</b> ommand
<b>DIGSI</b>	Parameterization system for SIPROTEC devices
<b>DNP</b>	<b>D</b> istributed <b>N</b> etwork <b>P</b> rotocol
<b>DP</b>	<b>D</b> ouble- <b>p</b> oint Indication
<b>Input data/ input direction</b>	Data from the DNP <b>slave to the DNP master</b> .
<b>Mapping</b>	Allocation of the SIPROTEC data objects to the DNP point index.
<b>Output data/ output direction</b>	Data from the DNP <b>master to the DNP slave</b> .
<b>RTU</b>	<b>R</b> emote <b>T</b> erminal <b>U</b> nit
<b>SC</b>	<b>S</b> ingle <b>C</b> ommand
<b>SP</b>	<b>S</b> ingle- <b>p</b> oint Indication



# Index

## Numerics

50HS .....	3-2
50N/51N .....	3-4
79 .....	3-3

## A

Additional support .....	0-ii
Alarm summary event .....	1-2
Analog Inputs .....	1-4, 3-10
Applicability of manual .....	0-ii

## B

Binary Input Points .....	1-2, 3-2
Binary Outputs / Commands .....	1-3, 3-8

## C

Caution (definition) .....	0-ii
Command output .....	1-3
continuous output .....	1-3
Control authority .....	1-3
Control mode .....	1-3
Copyright .....	1-ii

## D

Danger (definition) .....	0-ii
Device Profile Document .....	2-4
DNP messages .....	0-i
DNP V3.0 specification .....	0-i

## I

Implementation Table .....	2-2
----------------------------	-----

## M

Metered measurands .....	1-5
--------------------------	-----

## N

Note (definition) .....	0-ii
-------------------------	------

## P

Parameter names .....	0-iii
Parameter options .....	0-iii
Pulse output .....	1-3
pulse output .....	1-3

## Q

Qualified personnel (definition) .....	0-iii
----------------------------------------	-------

## S

Scaling of the metered measurands .....	1-5
Scaling values .....	1-4
Setting group .....	1-4
Stop data transmission .....	1-3
Subset Level 2 .....	2-2
Subset Level 3 .....	2-2
Summary alarm .....	1-2
Symbol conventions .....	0-iii

## T

Target audience of manual .....	0-i
Typographic conventions .....	0-iii

## V

Validity .....	0-ii
----------------	------

## W

Warning (definition) .....	0-ii
----------------------------	------



**To**

Siemens AG  
Dept. PTD PA D PSN  
D-13623 Berlin  
Germany

Dear reader,

printing errors can never be entirely eliminated:  
therefore, should you come across any when  
reading this manual, kindly enter them in this  
form together with any comments or suggestions  
for improvement that you may have.

**From**

Name:

Company/Dept.:

Address:

Phone no.:

Fax no.:

**Corrections/Suggestions**

Subject to technical alteration

---

Siemens Aktiengesellschaft

Copying of this document and giving it to others and the use or communication of the contents thereof, are forbidden without express authority. Offenders are liable to the payment of damages. All rights are reserved in the event of the grant of a patent or the registration of a utility model or design.

Order-no.: C53000-L1840-A014-03  
Available from: LZF Fürth-Bislohe  
Printed in Germany/Imprimé en Allemagne  
AG 0101 0.2 FO 123 En