

**SIEMENS**

***MK8000 OPC Server Interface***  
***Specification for Sistoro AX-MX-CX***

Data and design subject to change  
without notice. / Supply subject to  
availability.

© Copyright by  
Siemens Switzerland Ltd

We reserve all rights in this document and  
in the subject thereof. By acceptance of the  
document the recipient acknowledges these  
rights and undertakes not to publish the  
document nor the subject thereof in full or  
in part, nor to make them available to any  
third party without our prior express written  
authorization, nor to use it for any purpose  
other than for which it was delivered to him.

Sistore AX-MX-CX

---

Sistore AX - ( CCCOAPMN )

---

Multistate	Commands										
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man

1000 Quiet ✓

The Sistore connection is in normal.

---

1351 Anomaly Ack ✓

The MK8000 Server is not alligned with the Sistore.

---

1999 Fault Ack

The Sistore is not reacheable.

---

**Video In - ( CCCOVISU )**

---

This object represents the physical state of the Video Input

Multistate	Commands											
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man	2048-Status

950 Active



The Video In is recording

---

1000 Quiet



No abnormal conditions present.

---

1999 Fault Ack

The Video In is in Fault. The video signal is missing

---

## Digital Input - ( CCCODISU )

---

This object represents the physical state of the Digital input.

Multistate	Commands											
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man	2048-Status

950 Active

The Digital input is active

---

1000 Quiet

The digital input is not active.

---

## Digital Output - ( CCCODOSU )

---

This object represents the physical state of the digital output.

Multistate	Commands											
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man	2048-Status

950 Active

✓

The digital output is active.

---

1000 Quiet

✓

✓

The digital output is not active.

---

1100 Test

✓

The digital output is in pulse active state.

---

**Sistore MX - ( CCCOAPMN )**

---

This object represents the physical connection status with the Sistore MX

Multistate	Commands											
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man	2048-Status

1000 Quiet ✓

No abnormal conditions present.

---

1351 Anomaly Ack ✓

The MK8000 OPC Server is not aligned with the Sistore MX device

---

1999 Fault Ack

The Sistore MX is reachable for the MK8000 OPC Server.

---



**Sistore CX - ( CCCOAPMN )**

---

This object represents the physical connection status with the Sistore MX

Multistate	Commands											
	1-Ack	2-Reset	4-Arm	8-Disarm	16-Test	32-Active	64-Quiet	128-Disc	256-Conn	512-Block	1024-Man	2048-Status

1000 Quiet ✓

No abnormal conditions present.

---

1351 Anomaly Ack ✓

The MK8000 OPC Server is not aligned with the Sistore MX device

---

1999 Fault Ack

The Sistore MX is reachable for the MK8000 OPC Server.

---

Siemens Switzerland Ltd  
Building Technologies Group  
International Headquarters  
Fire Safety & Security Products  
Gubelstrasse 22  
CH-6301 Zug  
Tel +41 41 724 24 24  
Fax +41 41 724 35 22  
www.sbt.siemens.com

Document no. 009428\_d

Edition