


CATALOG NUMBER

ECMLK3225

electricCenter
ACCESSORIES

3 Phase Main Lug Kit
150A - 225A



0 40892 65190 4

MAIN LUG KIT INSTALLATION INSTRUCTIONS



⚠ DANGER

Hazardous Voltage.
Will cause death, serious injury
or substantial property damage.

Turn off power supplying this
equipment before working inside.

⚠ SAFETY INSTRUCTIONS

Note: This instruction outlines the
recommended installation procedure.
For installation by a qualified person,
as defined by all local electrical codes
and/or the National Electrical Code®.

1. Turn off and lock out the power supplying the load center before working inside.
2. Remove 1/4-20 nuts from bus studs and remove main breaker or main lugs.
3. Install lugs on bus studs as shown, fasten with 1/4-20 nuts (provided). Tighten to 40-45 lb-ins.
4. If necessary, obtain and install Main Breaker Filler Plate EC3PMFP1.

Siemens Industry, Inc. Norcross, Georgia U.S.A.

481000270101 Rev.A

® The National Electrical Code is a registered trademark of the National Fire Protection Association.

© 2011 Copyright Siemens Industry, Inc.

Assembled in Mexico

