

CATALOG NUMBER

# ECLK3

**electricCenter**  
ACCESSORIES

## Neutral Lug Kit #1 - 300 kcmil

Same As:

- LK3
- DLK3



## INSTALLATION INSTRUCTIONS



### ⚠ DANGER

**Hazardous Voltage.**  
Will cause death, serious injury  
or substantial property damage.

Turn off power supplying this  
equipment before working inside.



### SAFETY INSTRUCTIONS

1. Turn off and lock off the power supplying the load center before working inside.
2. Remove 3 screws from neutral bar at location desired for mounting lug kit.
3. Position lug on center hole.
4. Secure lug to neutral bar with flat head screw. Torque screw to 40-50 lb.-ins.
5. Insert set screw in lug.

**See wiring diagram for wire range size and tightening torque requirements.**

**Note:** This instruction outlines the recommended installation procedure.




SET SCREW



FLAT HEAD  
SCREW



LUG



© 2010 Copyright Siemens Industry, Inc.

Siemens Industry, Inc.

Norcross, Georgia U.S.A.

4810449 Rev.B

Assembled in Mexico