

## NOTES

# Introduction

This booklet will give you easy to follow instructions to allow you to set your **BUP2** Programmer to the Daily, (same ON/OFF times each day) program.


### Contents

- How do I change/set the clock?
- How do I change/set the ON/OFF times?
- How do I review the current ON/OFF times?
- What do the switching options mean?
- How do I select my Switching Options?
- How do I change summer and winter times?
- How do I set my holiday program?
- How do I activate my holiday program?
- What do the buttons do?

To commence programming first press the reset button using a ballpoint pen or similar tool the display should show as next page.

To make it easier to follow the buttons you should be using are coloured grey.

# BUP2 Daily



Display will flash as shown at first installation

## NOTES

## What do the buttons do?

### ADV (ADVANCE)





This brings forward the next switching time, for example:-




- if your times were ON 7am and OFF 9am - ON 5pm and OFF 10pm and you pressed the ADV at 4pm your heating would come ON straight away and go OFF at 10pm.
- if your times were ON 7am and OFF 9am - ON 5pm and OFF 10pm and you pressed the ADV at 9pm your heating would go OFF straight away and come ON at 7am the next morning.

### + HRS

This allows you to either increase your heating time in multiples of one hour (up to a maximum of 3 hours) during a timed ON period or to bring on the heating in multiples of one hour (up to a maximum of 3 hours) during an OFF period.



## How do I change/set the clock?

- Press top middle button  display shows 
- Alter time using  buttons to scroll
- When correct time is shown press press left hand button ENTER
- Press right hand button EXIT display shows 



## How do I change/set the ON/OFF times?







- Press left hand button MENU
- Press top middle button  $\triangle$  until SET PROGRAM is shown  
Press left hand button SELECT display will show SET CH
- Press left hand button SELECT display will show



(continued on next page)







## How do I activate my holiday program?

- Press left hand button MENU SET STATUS is shown, press SELECT
- Press top middle button  $\triangle$  until HOLIDAY is shown
- Press left hand button SELECT display will flash as shown  
your system is now in HOLIDAY mode (OFF) and will countdown the amount of days you have set it for, at the end of which it will automatically go back to your normal set program.  
You can also press CANCEL to return to normal program mode.




## How do I set my holiday program?




- Press left hand button MENU
- Press top middle button  $\triangle$  until SET HOLIDAY is shown
- Press left hand button SELECT display shows \_\_\_\_\_ number of holiday days will flash, change amount of days (1-99) by using  $\triangle$  +/ -  $\nabla$ , when desired amount of days is in the display press left hand button ENTER, then right hand button EXIT to return to MENU



To change 1st ON time for CH press SELECT, time will flash, change times by using  $\triangle$  +/ -  $\nabla$ , when desired time is in the display press ENTER display will show \_\_\_\_\_






- Repeat as above until last OFF time for CH is entered display will show \_\_\_\_\_ press middle top button SET HW is shown, repeat as above until all HW times have been entered, press BACK, then press EXIT to return to MENU



## How do I review the current ON/OFF times?





- Press left hand button MENU, press top middle button  $\triangle$  until REVIEW PROG is shown
- Press left hand button SELECT display shows CH PROGRAM VIEW Press VIEW
- 1st ON time for Central Heating (CH) will be shown

*(continued on next page)*



## How do I change winter and summer times?

- Press left hand button MENU
- Press top middle button  $\triangle$  until SET TIME is shown
- Press left hand button SELECT
- Alter time using  $\triangle$  +  $\nabla$  buttons until correct time is shown
- When correct time is shown press left hand button ENTER, then press right hand button EXIT to return to MENU display






- Press top middle button  $\triangle$  until your switching option is displayed




AUTO\*  
 MANUAL OFF\*  
 MANUAL ON\*  
 ONCE\*

\*see previous page for details

- Press left hand button ENTER, repeat for other selections (HW, CH etc)
- Press right hand button BACK
- Press right hand button EXIT  
 Display shows



- Press top middle button  $\triangle$   
 1st OFF will be shown
- Continue above two actions until all times have been reviewed press right hand button BACK, press top middle button  $\triangle$ . Display shows HW PROGRAM
- Press left hand button VIEW, press top middle button  $\triangle$ , 1st on time for (HW) Hot Water will be shown continue pressing top middle button until all HW times have been reviewed
- Press right hand button BACK, twice, then press right hand button EXIT (this will return you to MENU)



## What do the switching options mean?

### AUTO

This means that the BUP2 will switch ON and OFF according to the programmed times

### MANUAL OFF

This means that the BUP2 will be permanently OFF

### MANUAL ON

This means that the BUP2 will be permanently ON




### ONCE

This means that the BUP2 will switch ON at the first ON time and switch OFF at the last OFF time you have programmed ignoring any ON/OFF times in between. This is also referred to as All Day.

NB: Some older systems are not capable of having central heating ON when the hot water is OFF.

## How do I select my four switching options?

- Press left hand button MENU  
Display shows \_\_\_\_\_
- Press left hand button SELECT  
Display shows \_\_\_\_\_
- Press bottom middle button ▽ until correct selection is displayed (CH, HW or CH+HW)
- Press left hand button SELECT  
Display shows \_\_\_\_\_



(continued on next page)