

Heavy Duty Safety Switch Type VBII, 600 Amp, Type 1 (Indoor)

Standards and Ratings

- UL Listed under file #E4776
- Meets UL98 for switches and UL 50 for enclosures
- Meets NEMA Standard KS-1 for enclosed switches
- Meets NEC wire bending space requirements
- Rated 10,000 AIC with Class H fuses or 200,000 AIC with Class R, J and T fuses
- I²t rated (Amps² x Seconds = 6,000,000)
- 12X overload current rating exceeds 10X industry standard

• Suitable for use as service entrance equipment

Features

- Quick-make and break switching action
- Visible blade design
- Highly visible ON/OFF indication
- Modular design allows quick and easy replacement of parts
- Front removable lugs which can easily be converted to copper body or compression type lugs
- Defeatable dual cover interlock

General Information

Catalog Number	Volts	Description	Shipping Weight (lbs.)
HF226NH ¹	240	2 Pole, 3 Wire, Fusible	139
HF326NH	240	3 Pole, 4 Wire, Fusible	139
HF366H	600	3 Pole, 3 Wire, Fusible	138

Horsepower Ratings 2 3 - 240 Volts

Catalog 1 Phase,		240V AC	3 Phase,	3 Phase, 240V AC		250V
Number	Std	Max	Std	Max	DC	
HF226NH	15	15	75	200	50	
HF326NH	15	15	75	200	50	

Horsepower Ratings 1 2 3 - 600 Volts

Catalog	3 Phase, 480V AC		3 Phase, 60	OOV AC	
Number	Std	Max	Std	Max	
HF366H ⁴	150	400	200	500	

Mechanical Lug Wire Ranges (75°C, Cu/Al)

Description	Wire Range	
Line, Load Neutral	(2) 1/0 AWG - 500 Kcmil or (4) 1/0 AWG - 250 Kcmil	
Ground	(2) #6 AWG - 250 Kcmil	
200% Neutral	(4) #1/0 AWG - 500 Kcmil	
200% Ground	(4) #6 AWG - 300 Kcmil	

- 1 These switches are UL listed for application on grounded B systems.
- 2 Dual horsepower ratings: Std applies when non-time delay fuses are installed. Max - applies when time-delay fuses are installed.
- 3 Horsepower ratings listed also apply to Design E motors through 150HP at 240V, 300HP at 480V and 350HP at 600V with no derating.
- 4 Rated 50 HP on 3 phase, 240 AC systems.

Product Specification Sheet HD600.10

Answers for industry.

SIEMENS

Product Specification Sheet #HD600.10 (page 2 of 2)

Accessories

Catalog Number	Description
HA165678	One Normally Open and Closed Auxiliary Switches
HA265678	Two Normally Open and Closed Auxiliary Switches
HA365678	Low Voltage Auxiliary Switch
HG656	Equipment Ground Lug Kit
HG2656	Isolated Equipment Ground Lug Kit
HN656	Standard and 200% Neutral Kit
HN678	200% Neutral Kit
HR656	Class R Fuse Clip Kit (3 fuse clips per kit)
HLC65678	Copper Lug Kit (1 lug per kit)
HCL65678	Compression Lug Mounting Kit (1 kit/pole required,
	allows (1) lug/Ø)

Replacement Parts


Description	
Fusible Line Side Replacement Base	
Fusible Load Side Replacement Base	
Replacement Handle/Handle Guard	
Replacement Lug (1 lug per kit)	
Replacement Mechanism	
Replacement Door	
	Fusible Line Side Replacement Base Fusible Load Side Replacement Base Replacement Handle/Handle Guard Replacement Lug (1 lug per kit) Replacement Mechanism


Compression Lugs 4

Wire	Burndy		Thomas-Betts		Ilsco	
Size	CU Only	CU/AL	CU Only	CU/AL	CU Only	CU/AL
2/0	YA26-N	YA26-A1	54160 54951BE			IACL-2/0 ACN-2/0
3/0	YA27-L Box YA27	YA27A3	54165-TB 54965BE		CRB-3/0 CRB-3/0L	IACL-3/0 ACN-3/0
4/0	YA28-L Box YA28	YA28A3	54170 54970BE	60150	CRB-4/0 CRB-4/0L	IACL-4/0 ACN-4/0
250 Kcmil	YA29-L Box YA29	YA29A1	54113 54913BE	61156 60156	CRA-250 CRA-250L	IACL-250 ACL-250
300 Kcmil	YA30-L YA30	YA30A1	54114 54914BE	61162 60162	CRA-300 CRA-300L	IACL-300 ACL-300


¹Each Line and Load Replacement Base contains one pole.

Dimension Drawing





KNOCKOUT	CONDUIT
CODE	SIZE
A (Tangential)	2.00 2.50 3.00 3.50



	LINE SIDE WIRE BEND	LOAD SIDE WIRE BEND	
240V fused	11.07 (281)	13.85 (352)	
600V fused	11.07 (281)	11.07 (281)	

Enclosure: Cold Rolled Steel .075 (14 Gauge) Finish: ANSI Grey #61 Paint

² Lugs are not provided on Line and Load Replacement Base Assemblies. Order Lug Kit.

³ Place "DOOR" at the end of the switch catalog number.

⁴ If compression lugs are used, order compression lug kit HCL65678.