

# SIEMENS

Ingenuity for life

## SIPROTEC 6MU85

Merging Unit

[www.siemens.com/6MU85](http://www.siemens.com/6MU85)

### Description

The new SIPROTEC 6MU85 Merging Unit based on the flexible SIPROTEC 5 system has been designed for conventional and non-conventional instrument transformers (LPITs)\* and digitalizes all primary data close to the process. SIPROTEC 5 process bus provides versatile solutions and migration concepts for new and existing systems.

Main function	Merging Unit, Breaker functions, Backup protection functions, Additional functions
Communication	Up to 4 sampled measured value streams according IEC 61850-9-2LE or IEC 61850-9-2 / IEC 61869 flexible streams
Hardware flexibility	Flexibly adjustable and expandable I/O quantity structure within the scope of the modular SIPROTEC 5 system; 1/6 expansion modules can be added.
Housing width	1/3 × 19 inches to 2/1 × 19 inches
As standard	Conformal Coating

### Applications

Merging Unit for

- Analog and digital feeder values
- Central Merging Unit for transformers
- Central protection
- Bay units for distributed busbar protection
- Fault recorder for process bus
- Centralized synchrocheck



SIPROTEC 6MU85

### Functions

#### Merging Unit

- Per ETH-BD-2FO Ethernet module 1 or 2\* Sampled Measured Value (SMV) streams  
- up to 32 analog values in any combination of CTs and VTs  
or  
- 4x CTs, 4x VTs (IEC 61850-9-2LE)
- Up to 4 ETH-BD-2FO modules possible
- Reliable and redundant data transmission via PRP protocol
- IEC 61869-9, IEC 61869-13 compliant
- IEC 61850-8-1 GOOSE, MMS and Merging Unit protocol on the same Ethernet module
- Sample and date/time synchronization via IEEE 1588v2/PTP
- Redundant power supply
- Extended temperature range (-40 °C to 70 °C)

Merging Unit functionality is also available for all modular SIPROTEC 5 protection devices.

# Efficient and modular

## Breaker functions

- Control with switchgear interlocking
- Circuit-breaker failure protection (50BF)
- Circuit-breaker wear monitoring
- Switching statistics
- Point on wave switching (PoW)
- Trip-circuit supervision (74TC)
- Automatic reclosing (79)
- Synchrocheck (25)

## Backup protection functions

- Non-directional overcurrent protection (50/51, 50N/51N)
- Directional overcurrent protection (67/67N)
- Overvoltage and undervoltage protection (27/59)

## Additional functions

- Phasor Measurement Unit (PMU) for synchrophasor measured values and IEEE C37.118 protocol
- Arc protection
- Auxiliary functions for simple tests and commissioning
- Temperature measurement via Thermobox TR1200 (7XV5662-6AD10 or 7XV5662-8AD10)
- 4-20 mA transducer inputs for various analog process values, e.g. pressure, tap-changer position

## Communication

- Pluggable communication modules, usable for different and redundant protocols (IEC 61850-8-1,

IEC 61850-9-2, IEC 60870-5-103, IEC 60870-5-104, Modbus TCP, DNP3 serial and TCP, PROFINET IO)

- Serial protection data communication via optical fibers, two-wire connections and communication networks (IEEE C37.94, and others), including automatic switchover between ring and chain topology
- Extensive cyber security functionality, such as role-based access control (RBAC), protocolling security-related events or signed firmware
- Simple, quick and secure access to device data via a standard Web browser – without additional software

## Benefits

- Adaptable to multiple CT, VT, LPIT\* inputs
- Scalable number of binary inputs and outputs
- Expandable by a 2nd row
- Direct “high speed” tripping of circuit breaker < 1 ms
- Collection of additional data (temperature, pressure, tap changer positions, ...)
- Cyber security in accordance with NERC CIP and BDEW Whitepaper requirements
- Highest availability even under extreme environmental conditions by “conformal coating” of electronic boards

\*) in preparation

LPIT = Low Power Instrument Transformer



Siemens 2020  
Smart Infrastructure  
Digital Grid  
Humboldtstrasse 59  
91459 Nuremberg,  
Germany

For the U.S. published by  
Siemens Industry Inc.

100 Technology Drive  
Alpharetta, GA 30005  
United States

Customer Support: <http://www.siemens.com/csc>

© Siemens 2020. Subject to changes and errors.  
SIPROTEC 6MU85 profile.pdf

For all products using security features of OpenSSL, the following shall apply:

This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit ([www.openssl.org](http://www.openssl.org)), cryptographic software written by Eric Young ([eay@cryptsoft.com](mailto:eay@cryptsoft.com)) and software developed by Bodo Moeller.